

ECO INDUSTRIAL SUPPLIES

3 Andrew Street Christie Downs South Australia 5164

Phone +0061 (0) 458 158 777

ABN: 25 145 151 241

GLC-6S Cordless Cap Lamp



Care Instructions

Fully charge before use.

If storing for long periods fully discharge and charge every 2 months to keep your batteries in good condition.

Thank you for purchasing our GLC-6S Cap Lamp.

Great care has gone into assembly and selecting high quality components to help ensure your underground safety. Please look after me and I will serve you long time. :)

Features

Item	Value
Model	GLC-6S cordless cap lamp
Light source	one main light two auxiliary lights
Battery Capacity	6.8Ah
Rated Voltage	3.7V
Main light current	400mA - 530mA - 1000mA
Power of main light	2.96W
Illuminous	385lum
Brightness	9000lux - 14000lux - 18000lux
Life span of main light	100000hrs
Battery cycles	1200 cycles
Working time	17hrs - 13hrs - 6hrs
Weight	245g
Water-proof grade	IP68

OLED screen for time , date, battery capacity, logo or other information display .

18000lux strong brightness with good optical lighting spot.

Adjustable stainless steel clip for lighting angle change.

Magnetic lighting sport with IP68 water-proof and support USB charging.

Small size and light weight. More handy switch for convenient touching.

Anti-explosive, flame-resistant, impact-resistant, IP68 water-proof.

Settings.

To set time and date hold down display button for 3 seconds until it flashes.

Display button will now scroll through hour, min, year, month, day.

Use the lighting button to set correct time and date.

When finished long press the display button again to exit set up mode.

